

# BIOS/EC flash instruction

EH20GM

Date of Create: 2019/08/08

ELITEGROUP COMPUTER SYSTEMS CO., LTD.

 <b>ELITEGROUP</b>	<b>Instruction</b>
精英電腦 股份有限公司	<b>BIOS/EC flash</b>
Pages: 2 of 2	

**Use one of the methods to flash BIOS/EC.**

### **A. Windows x64:**

1. Plug-in adapter and power-on the system to OS, make sure system power is supplied by AC adapter.
2. Copy the BIOS file package to the system and unzip it.
3. Run [WF.bat as administrator](#) for f/w upgrading.

### **B. Build-in EFI Shell:**

1. Prepare an USB key. (Format to FAT or FAT32 type first)
2. Unzip the BIOS file package to the USB key
3. Insert the USB key to the USB port.
4. Plug-in an adapter and power-on or reboot the system to POST (Power On Self test) screen.
5. Press [<F7>](#) key to launch Boot Menu.
6. Select Build-in EFI Shell and press [<ENTER>](#) key.
7. Run [SF.nsh](#) for f/w upgrade.

For example: Assume [SF.nsh](#) can be found in **BIOS package**, type the commands as below)

```
Shell> fs3:                <ENTER>
fs3:\> SF.nsh             <ENTER>
```

*Note. fs3=Shell mode default disk number.*

*Different disk configurations will have different disk numbers.*